USB TO RS485 CONVERTER

ITEM NO.: RS003




The RS003 USB Converter provides an easy solution for adding new or additional Com Ports to Windows or Macintosh computers through their USB ports. The RS485 connection is 2- pin terminal connector. The unit is powered from the USB connection, so no external power supply is necessary.

Features:

- USB to RS485 interface converter.
- Two wire, differential signals, half duplex.
- Non power operation.
- Auto switching baud rate, speed up to 115, 200 baud over a distance 1200 meters.
- 32 units connected together in RS485 multi drop installations.
- USB 2.0 Compliant.
- Powered by PC.
- Connect/Disconnect Without Reboot.
- Windows 98, ME, XP & 2000 Compatible.
- MAC OS 8.6 to 9.2 Compatible.
- Software Drivers Included.

Installation View:



Specification:

| ITEM NO. | | RS003 |
|------------------------|--------------|---|
| Input | | USB 2.0 |
| Output | | RS485 |
| Input/Output interface | | USB B Type x 1 [,] 2 pint terminal x 1 |
| Power Consumption | | 10mA (max) from the USB connector |
| Transmission Distance | | 1.2km |
| Temperature | | Operation: $0 \sim 55^{\circ}$ C, Storage: $-20 \sim 70^{\circ}$ C, Humidity: up to 95% |
| Dimensions | W x H x D mm | 54.6*25.4*25.4 |
| Weight | g | 45 |
| RoHS (| E F© C | Rev B |

Rev. B

Terminal